



EPA-120WMA

1 ZONE MIXER AMPLIFIER

Features

- Overheat warning and protection system
- XLR and 6.35mm link connectivity
- Amplifier link input for expansion
- Balanced input with no grounding noise
- Five LED status indication system
- 100V and 0dB input compatibility

Description

EKA VIS EPA-120WMA is a reliable Mixer Amplifier designed to enhance and extend audio output in professional PA and emergency voice evacuation systems. It supports transformer isolated 100V, 70V and 4–16Ω outputs, ensuring flexible system integration. With balanced input and 100V/0dB compatibility, it delivers stable, noise-free signal amplification across installations.

EKA VIS EPA-120WMA features LED status indicators for real-time monitoring, along with XLR and 6.35 mm jack connectivity for easy amplifier linking and expansion. Built-in protection against short circuit and overheating ensures safe operation, while its high-power design enables consistent performance in demanding environments.

Technical Specification

Operating Voltage	220–240V AC (50/60Hz)
Rated Power Output	120W
Line Voltage	70-100V
Output Impedence	4-16Ω
Frequency Respones	60Hz-15KHz
Dimension	406mmx279mmx140mm
Approximate Weight	11.7 Kg

Ordering Information

EPA-120WMA	1 Zone Mixer Amplifier
------------	------------------------

EKA VIS LIMITED

71-75 Shelton Street, Covent Garden,
London-WC2H9JQ
United Kingdom
E - info@ekavis.com

